# ASSR-4118 , ASSR-4119 and ASSR-4128

Form A, Solid State Relay (Photo MOSFET) (400V/0.10A/35 $\Omega$ )



# **Data Sheet**



### Description

The ASSR-41XX Series consists of an AlGaAs infrared light-emitting diode (LED) input stage optically coupled to a high-voltage output detector circuit. The detector consists of a high-speed photovoltaic diode array and driver circuitry to switch on/off two discrete high voltage MOSFETs. The relay turns on (contact closes) with a minimum input current of 3mA through the input LED. The relay turns off (contact opens) with an input voltage of 0.8V or less.

The single channel configurations, ASSR-4118 and ASSR-4119, are equivalent to 1 Form A Electromechanical Relays (EMR), and the dual channel configuration, ASSR-4128, is equivalent to 2 Form A EMR. They are available in 4-pin SO, 6-pin DIP, 8-pin DIP and Gull Wing Surface Mount for DIP packages. ASSR-4119 enables AC/DC and DC-only output connections. For DC-only connection, the output current, lo, increases to 0.2A and the on-resistance, R(ON) reduces to  $10\Omega$ .

#### **Applications**

- Telecommunication Switching
- Data Communications
- Industrial Controls
- Medical
- Security
- EMR / Reed Relay Replacement

#### Features

- Compact Solid-State Bi-directional Signal Switch
- Single and Dual Channel Normally-off Single-Pole-Single-Throw (SPST) Relay
- 400V Output Withstand Voltage
- 0.1A or 0.2A Current Rating (See Schematic for ASSR-4119 Connection A and B)
- Low Input Current: CMOS Compatibility
- Low On-Resistance: 8Ω Typical for DC-only, 25Ω Typical for AC/DC
- High Input-to-Output Insulation Voltage (Safety and Regulatory Approvals Pending)
  - 3750 Vrms for 1 min per UL1577
  - CSA Component Acceptance

#### **Functional Diagram**



CAUTION: It is advised that normal static precautions be taken in handling and assembly of this component to prevent damage and/or degradation which may be induced by ESD.

### **Ordering Information**

ASSR-xxxx is UL Recognized with 3750 Vrms for 1 minute per UL1577 and is approved under CSA Component Acceptance Notice #5.

	Option	_				
Part number	<b>RoHS Compliant</b>	Package	Surface Mount	Gull Wing	Tape & Reel	Quantity
ACCD 4110	-003E	60 A	Х			100 units per tube
ASSR-4118	-503E	- SO-4	Х		Х	1500 units per reel
	-001E					50 units per tube
ASSR-4119	-301E	300mil DIP-6	Х	Х		50 units per tube
	-501E	_	Х	Х	Х	1000 units per reel
	-002E					50 units per tube
ASSR-4128	-302E	- 300 mil DIP-8	Х	Х		50 units per tube
	-502E	_	Х	Х	Х	1000 units per reel

To order, choose a part number from the part number column and combine with the desired option from the option column to form an order entry.

#### Example 1:

ASSR-4119-501E to order product of 300mil DIP-6 Gull Wing Surface Mount package in Tape and Reel packaging and RoHS Compliant.

#### Example 2:

ASSR-4128-002E to order product of 300mil DIP-8 package in tube packaging and RoHS Compliant.

Option datasheets are available. Contact your Avago sales representative or authorized distributor for information.

#### **System Schematics**

#### ASSR-4118



# System Schematics (Continued)

# **ASSR-4119 Connection A**



# **ASSR-4119 Connection B**



ASSR-4128





#### **Package Outline Drawings**



#### ASSR-4118 4-Pin Small Outline Package





(0.040)

2.66 (0.105) MIN. \*

0.45 (0.018)

0.65 (0.025)

2.28 (0.090) 2.80 (0.110)

[0.02]

0.5

 $[0.004 \pm 0.004]$ 

0.102 ± 0.102

[ 0.02 ] ŀ

0.5

**DIMENSIONS IN MILLIMETERS AND (INCHES).** 

2.16 (0.085)

2.54 (0.100)



#### ASSR-4119 6-Pin DIP Package with Gull Wing Surface Mount Option 300

NOTE: FLOATING LEAD PROTRUSION IS 0.25 mm (10 mils) MAX.

#### ASSR-4128 8-Pin DIP Package





DIMENSIONS IN MILLIMETERS AND (INCHES). OPTION NUMBERS 300 AND 500 NOT MARKED.





NOTE: FLOATING LEAD PROTRUSION IS 0.25 mm (10 mils) MAX.

**Lead Free IR Profile** 



Non-halide flux should be used

# **Regulatory Information**

The ASSR-4118, ASSR-4119 and ASSR-4128 are approved by the following organizations:

# UL

Approved under UL 1577, component recognition program up to  $V_{\text{ISO}}$  = 3750  $V_{\text{RMS}}$ 

# CSA

Approved under CSA Component Acceptance Notice #5.

# Insulation and Safety Related Specifications

			ASSR-4119		
Parameter	Symbol	ASSR-4118	ASSR-4128	Units	Conditions
Minimum External Air Gap (Clearance)	L(101)	4.9	7.1	mm	Measured from input terminals to output terminals, shortest distance through air.
Minimum External Tracking (Creepage)	L(102)	4.9	7.4	mm	Measured from input terminals to output terminals, shortest distance path along body.
Minimum Internal Plastic Gap (Internal Clearance)		0.08	0.08	mm	Through insulation distance conductor to conductor, usually the straight line distance thickness between the emitter and detector.
Tracking Resistance (Comparative Tracking Index)	CTI	175	175	V	DIN IEC 112/VDE 0303 Part 1
Isolation Group (DIN VDE0109)		Illa	Illa		Material Group (DIN VDE 0109)

# **Absolute Maximum Ratings**

Parameter		Symbol	Min.	Max.	Units	Note
Storage Temperature		Ts	-55	125	°C	
Operating Temperature		T <sub>A</sub>	-40	85	°C	
Junction Temperature		Тյ		125	°C	
Lead Soldering Cycle	Temperature			260	°C	
	Time			10	S	
Input Current	Average	I <sub>F</sub>		25	mA	
	Surge			50		
	Transient			1000		
Reversed Input Voltage		V <sub>R</sub>		5	V	
Input Power Dissipation	ASSR-4118	P <sub>IN</sub>		40	mW	
	ASSR-4119	PIN		40	mW	
	ASSR-4128	P <sub>IN</sub>		80	mW	
Output Power Dissipation	ASSR-4118	Po		300	mW	
	ASSR-4119	Po		300	mW	
	ASSR-4128	Po		600	mW	
Average Output Current		lo		0.10	А	1
$(T_A = 25^{\circ}C, T_C \le 100^{\circ}C)$	ASSR-4119 Connection B	lo		0.20	A	1
Output Voltage (T <sub>A</sub> = 25°C)		Vo	-400	400	V	2
	ASSR-4119 Connection B	Vo	0	400	V	
Solder Reflow Temperature Pro	ofile	See Lead F	ree IR Profile			

# **Recommended Operating Conditions**

Parameter	Symbol	Min.	Max.	Units	Note
Input Current (ON)	I <sub>F(ON)</sub>	3	20	mA	3
Input Voltage (OFF)	V <sub>F(OFF)</sub>	0	0.8	V	
Operating Temperature	T <sub>A</sub>	-40	+85	°C	

# Package Characteristics

Unless otherwise specified,  $T_A = 25^{\circ}C$ .

Parameter	Sym.	Min.	Тур.	Max.	Units	Conditions	Note
Input-Output Momentary Withstand Voltage	V <sub>ISO</sub>	3750			Vrms	RH≤50%, t = 1 min	4, 5
Input-Output Resistance	R <sub>I-O</sub>		10 <sup>12</sup>		Ω	$V_{I-O} = 500 \text{ Vdc}$	
Input-Output Capacitance	ASSR-4118 C <sub>I-O</sub>		0.4		pF	f = 1 MHz; V <sub>I-O</sub> = 0 Vdc	4
	ASSR-4119 C <sub>I-O</sub>		0.5		pF	f = 1 MHz; V <sub>I-O</sub> = 0 Vdc	
	ASSR-4128 C <sub>I-O</sub>		0.8		pF	f = 1 MHz; V <sub>I-O</sub> = 0 Vdc	

# **Electrical Specifications (DC)**

For operating  $T_A = +25^{\circ}C$ 

Parameter	Sym.	Min.	Тур.	Max.	Units	Conditions	Fig.	Note
Output Withstand Voltage	VO(OFF)	400	450		V	$V_F$ =0.8V, $I_O$ =250 $\mu$ A	5	
Output Leakage Current	I <sub>O(OFF)</sub>		0.005	1	μΑ	$V_{\rm F}$ =0.8V, $V_{\rm O}$ =400V		
Input Reverse Breakdown Voltage	V <sub>R</sub>	5			V	I <sub>R</sub> =10 μA		
Input Forward Voltage	V <sub>F</sub>	1.1	1.3	1.6	V	I <sub>F</sub> =5mA	6, 7	
Output On-resistance	R <sub>(ON)</sub>		25	35	Ω	I <sub>F</sub> =5mA, I <sub>O</sub> =100mA, Pulse ≤30ms	8, 9	6
	ASSR-4119 Connection B		8	10	Ω	I <sub>F</sub> =5mA, I <sub>O</sub> =200mA, Pulse ≤30ms		

### Switching Specifications (AC)

#### For operating $T_A = +25^{\circ}C$

Parameter	Sym.	Min.	Тур.	Max.	Units	Conditions	Fig.	Note
Turn On Time	T <sub>ON</sub>		0.7	5.0	ms	I <sub>F</sub> =5mA, I <sub>O</sub> =100mA		
Turn Off Time	T <sub>OFF</sub>		0.04	5.0	ms	I <sub>F</sub> =5mA, I <sub>O</sub> =100mA		

Notes:

1. For derating, refer to Figure 1, 2, 3 and 4.

2. The voltage across the output terminals of the relay should not exceed this rated withstand voltage. Over-voltage protection circuits should be added in some applications to protect against over-voltage transients.

3. Threshold to switch device is  $I_F \ge 0.5$ mA, however, for qualified device performance over temperature range, it is recommended to operate at  $I_F = 5$ mA.

4. Device is considered as a two terminal device:

ASSR-4118 - pin 1, 2 shorted and pin 3, 4 shorted.

ASSR-4119 - pin 1, 2, 3 shorted and pin 4, 5, 6 shorted. ASSR-4128 - pin 1, 2, 3, 4 shorted and pin 5, 6, 7, 8 shorted.

- 5. The Input-Output Momentary Withstand Voltage is a dielectric voltage rating that should not be interpreted as an input-output continuous voltage rating. For the continuous voltage rating refer to the IEC/EN/DIN EN 60747-5-2 Insulation Characteristics Table (if applicable), your equipment level safety specification, or Avago Technologies Application Note 1074, "Optocoupler Input-Output Endurance Voltage."
- 6. During the pulsed  $R_{(ON)}$  measurement (I<sub>O</sub> duration  $\leq$ 30ms), ambient (T<sub>A</sub>) and case temperature (T<sub>C</sub>) are equal.

#### **Application Information**

#### **On-Resistance and Derating Curves**

The Output On-Resistance,  $R_{(ON)}$ , specified in this data sheet, is the resistance measured across the output contact when a pulse current signal (lo=100mA) is applied to the output pins. The use of a pulsed signal ( $\leq$ 30ms) implies that each junction temperature is equal to the ambient and case temperatures. The steady-state resistance, Rss, on the other hand, is the value of resistance measured across the output contact when a DC current signal is applied to the output pins for a duration sufficient to reach thermal equilibrium. Rss includes the effects of the temperature rise in the device.

Figure 1, 2, 3 and 4 specify the maximum average output current allowable for a given ambient temperature. The maximum allowable output current and power dissipation are related by the expression Rss =  $Po(max)/(lo(max))^2$  from which Rss can be calculated. Staying within the safe area assures that the steady state MOS-FET junction temperature remains less than 125 °C.



Figure 1. Maximum Output Current Rating vs Ambient Temperature (ASSR-4118-003E)



Figure 3. Maximum Output Current Rating vs Ambient Temperature (ASSR-4119-001E DC Connection)



Figure 2. Maximum Output Current Rating vs Ambient Temperature (ASSR-4119-001E)



Figure 4. Maximum Output Current Rating vs Ambient Temperature (ASSR-4128-002E)



Figure 5. Normalized Output Withstand Voltage vs Temperature



Figure 7. Typical Forward Current vs Forward Voltage



Figure 9. Typical Output Current vs Output Voltage



Figure 6. Typical Forward Voltage vs Temperature



Figure 8. Typical on Resistance vs Temperature

For product information and a complete list of distributors, please go to our web site: www.avagotech.com

Avago, Avago Technologies, and the A logo are trademarks of Avago Technologies in the United States and other countries. Data subject to change. Copyright © 2005-2012 Avago Technologies. All rights reserved. AV02-0218EN - March 19, 2012

