

LM139, LM239, LM339

Low-power quad voltage comparators

Features

- Wide single supply voltage range or dual supplies for all devices: +2 to +36 V or ±1 V to ±18 V
- Very low supply current (1.1 mA) independent of supply voltage
- Low input bias current: 25 nA typ
- Low input offset current: ±5 nA typ
- Low input offset voltage: ±1 mV typ
- Input common-mode voltage range includes ground
- Low output saturation voltage: 250 mV typ; (I_{SINK} = 4 mA)
- Differential input voltage range equal to the supply voltage
- TTL, DTL, ECL, MOS, CMOS compatible outputs

Description

This family of devices consists of four independent precision-voltage comparators with an offset voltage specification as low as 2 mV maximum for LM339A, LM239A and LM139A. Each comparator has been designed specifically to operate from a single power supply over a wide range of voltages. Operation from split power supplies is also possible.

These comparators also have a unique characteristic in that the input common mode voltage range includes ground even though operated from a single power supply voltage.



1 Schematic diagram



Figure 1. LM139 schematic diagram (1/4)



2 Absolute maximum ratings and operating conditions

Symbol	Parameter	Value	Unit
V _{CC}	Supply voltage	±18 or 36	V
V_{ID}	Differential input voltage	±36	V
V _{IN}	Input voltage	-0.3 to +36	V
	Output short-circuit to ground ⁽¹⁾	Infinite	
R _{thja}	Thermal resistance junction to ambient ⁽²⁾ DIP14 SO-14 TSSOP14	80 105 100	°C/W
R _{thjc}	Thermal resistance junction to case ⁽²⁾ DIP14 SO-14 TSSOP14	33 31 32	°C/W
T _{stg}	Storage temperature range	-65 to +150	°C
Тj	Junction temperature	+150	°C
T _{LEAD}	Lead temperature (soldering 10 seconds)	260	°C
	Human body model (HBM) ⁽³⁾	500	
ESD	Machine model (MM) ⁽⁴⁾	100	V
	Charged device model (CDM) ⁽⁵⁾	1500	

Table 1.	Absolute maximum ratings
	libeerate maximum ratinge

1. Short-circuits from the output to V_{CC}^+ can cause excessive heating and eventual destruction. The maximum output current is approximately 20 mA independent of the magnitude of V_{CC}^+ .

2. Short-circuits can cause excessive heating. These values are typical.

3. Human body model: a 100 pF capacitor is charged to the specified voltage, then discharged through a 1.5 k Ω resistor between two pins of the device. This is done for all couples of connected pin combinations while the other pins are floating.

- 4. Machine model: a 200 pF capacitor is charged to the specified voltage, then discharged directly between two pins of the device with no external series resistor (internal resistor < 5 Ω). This is done for all couples of connected pin combinations while the other pins are floating.
- 5. Charged device model: all pins and the package are charged together to the specified voltage and then discharged directly to the ground through only one pin. This is done for all pins.

Symbol	Parameter	Value	Unit
V _{CC}	Supply voltage	2 to 32 ±1 to ±16	V
V _{ICM}	Common mode input voltage range	0 to (V _{CC} ⁺ - 1.5)	V
T _{oper}	Operating free-air temperature range – LM139, LM139A – LM239, LM239A – LM339, LM339A	-55, +125 -40, +105 0, +70	°C

Table 2. Operating conditions ($T_{amb} = 25^{\circ} C$)



3 Electrical characteristics

Table 3.Electrical characteristics at $V_{CC}^+ = +5 V$, $V_{CC}^- = GND$, $T_{amb} = +25^{\circ} C$
(unless otherwise specified)

Symbol	Parameter	Parameter LM139A - LM239A LM339A			LI	LM239 39	Unit	
			Тур.	Max.	Min	Тур.	Max.	
V _{IO}	Input offset voltage ⁽¹⁾ T _{min} ≤T _{amb} ≤T _{max}		1	2 4		1	5 9	mV
I _{IO}	Input offset current T _{min} ≤T _{amb} ≤T _{max}		3	25 100		5	50 150	nA
I _{IB}	Input bias current (I ⁺ or I ⁻) ⁽²⁾ T _{min} ≤T _{amb} ≤T _{max}		25	100 300		25	250 400	nA
A _{VD}	Large signal voltage gain V_{CC} = 15 V, R_L = 15 kΩ, V_o = 1 V to 11 V	50	200		50	200		V/mV
I _{CC}	Supply current (all comparators) $V_{CC} = +5$ V, no load $V_{CC} = +30$ V, no load		1.1 1.3	2 2.5		1.1 1.3	2 2.5	mA
V _{ICM}	Input common mode voltage range $^{(3)}$ V _{CC} = 30 V T _{min} \leq T _{amb} \leq T _{max}	0 0		V _{CC} ⁺ -1.5 V _{CC} ⁺ -2	0 0		V _{CC} ⁺ -1.5 V _{CC} ⁺ -2	v
V _{ID}	Differential input voltage ⁽⁴⁾			V _{CC} ⁺			V _{CC} ⁺	V
V _{OL}	Low level output voltage V_{ID} = -1 V, I_{SINK} = 4 mA $T_{min} \leq T_{amb} \leq T_{max}$		250	400 700		250	400 700	mV
I _{ОН}			0.1	1		0.1	1	nA μA
I _{SINK}	Output sink current V_{ID} = 1 V, V ₀ = 1.5 V	6	16		6	16		mA
t _{re}	Response time $^{(5)}$ R _L = 5.1 k Ω connected to V _{CC} ⁺		1.3			1.3		μs



Table 3.Electrical characteristics at $V_{CC}^+ = +5 V$, $V_{CC}^- = GND$, $T_{amb} = +25^{\circ} C$ (unless otherwise specified) (continued)

Symbol	pol Parameter		LM139A - LM239A LM339A		LM139 - LM239 LM339			Unit
		Min.	Тур.	Max.	Min	Тур.	Max.	
trel	Large signal response time R_L = 5.1 k Ω connected to V_{CC}^+ , e_l = TTL, $V_{(ref)}$ = +1.4 V		300			300		ns

1. At output switch point, $V_0 \approx 1.4$ V, V_{CC}^+ from 5 V to 30 V, and over the full common-mode range (0 V to V_{CC}^+ -1.5 V).

The direction of the input current is out of the IC due to the PNP input stage. This current is essentially constant, independent of the state of the output, so no loading charge exists on the reference of input lines.

 The input common-mode voltage of either input signal voltage should not be allowed to go negative by more than 0.3 V. The upper end of the common-mode voltage range is V_{CC}⁺ -1.5 V, but either or both inputs can go to +30 V without damage.

4. Positive excursions of input voltage may exceed the power supply level. As long as the other voltage remains within the common-mode range, the comparator will provide a proper output state. The low input voltage state must not be less than -0.3 V (or 0.3 V below the negative power supply, if used).

5. The response time specified is for a 100 mV input step with 5 mV overdrive. For larger overdrive signals, 300 ns can be obtained.



Electrical characteristics curves 4



Figure 4. Output saturation voltage vs. output current



Figure 6. Response time for various input overdrives - positive transition



Figure 3. Input current vs. supply voltage

Figure 5. Response time for various input overdrives - negative transition 6 Input overdrive : 5mV 5





5 Typical applications









Figure 12. Transducer amplifier



Figure 11. Low frequency op amp





Figure 13. Time delay generator



Figure 14. Low frequency op amp with offset Figure 15. Zero crossing detector (single adjust

power supply)









Figure 17. Limit comparator





Figure 20. Comparator with a negative reference





6 Package information

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK[®] packages, depending on their level of environmental compliance. ECOPACK[®] specifications, grade definitions and product status are available at: www.st.com. ECOPACK[®] is an ST trademark.



6.1 DIP14 package information





Table 4.	DIP14 package mechanical data
----------	-------------------------------

	Dimensions					
D-4		Millimeters			Inches	
Ref.	Min.	Тур.	Max.	Min.	Тур.	Max.
А			5.33			0.21
A1	0.38			0.015		
A2	2.92	3.30	4.95	0.11	0.13	0.19
b	0.36	0.46	0.56	0.014	0.018	0.022
b2	1.14	1.52	1.78	0.04	0.06	0.07
С	0.20	0.25	0.36	0.007	0.009	0.01
D	18.67	19.05	19.69	0.73	0.75	0.77
Е	7.62	7.87	8.26	0.30	0.31	0.32
E1	6.10	6.35	7.11	0.24	0.25	0.28
е		2.54			0.10	
e1		15.24			0.60	
eA		7.62			0.30	
eB			10.92			0.43
L	2.92	3.30	3.81	0.11	0.13	0.15



6.2 SO-14 package information



Figure 22. SO-14 package mechanical drawing

Table 5. SO-14 package mechanical data

	Dimensions						
D-4		Millimeters			Inches		
Ref.	Min.	Тур.	Max.	Min.	Тур.	Max.	
А	1.35		1.75	0.05		0.068	
A1	0.10		0.25	0.004		0.009	
A2	1.10		1.65	0.04		0.06	
В	0.33		0.51	0.01		0.02	
С	0.19		0.25	0.007		0.009	
D	8.55		8.75	0.33		0.34	
E	3.80		4.0	0.15		0.15	
е		1.27			0.05		
Н	5.80		6.20	0.22		0.24	
h	0.25		0.50	0.009		0.02	
L	0.40		1.27	0.015		0.05	
k		•	8° (r	nax.)	•	•	
ddd			0.10			0.004	



6.3 TSSOP14 package information



Figure 23. TSSOP14 package mechanical drawing

Table 6. TSSOP14 package mechanical data

			Dime	nsions		
Ref.		Millimeters			Inches	
	Min.	Тур.	Max.	Min.	Тур.	Max.
Α			1.20			0.047
A1	0.05		0.15	0.002	0.004	0.006
A2	0.80	1.00	1.05	0.031	0.039	0.041
b	0.19		0.30	0.007		0.012
С	0.09		0.20	0.004		0.0089
D	4.90	5.00	5.10	0.193	0.197	0.201
E	6.20	6.40	6.60	0.244	0.252	0.260
E1	4.30	4.40	4.50	0.169	0.173	0.176
е		0.65			0.0256	
L	0.45	0.60	0.75	0.018	0.024	0.030
L1		1.00			0.039	
k	0°		8°	0°		8°
aaa			0.10			0.004



Ordering information 7

LM339ADT

LM339PT

LM339APT

Part number	Temperature range	Package	Packing	Marking
LM139N LM139AN		DIP14	Tube	LM139N LM139AN
LM139D LM139AD	55° C 105° C	SO-14	Tube	139 139A
LM139DT LM139ADT	55° C, +125° C	SO-14	Tape & reel	139 139A
LM139PT LM139APT	-	TSSOP14	Tape & reel	139 139A
LM239N LM239AN		DIP14	Tube	LM239N LM239AN
LM239D LM239AD		SO-14	Tube	239 239A
LM239DT LM239ADT	40° C, +105° C	SO-14	Tape & reel	239 239A
LM239PT LM239APT		TSSOP14	Tape & reel	239 239A
LM339N LM339AN		DIP14	Tube	LM339N LM339AN
LM339D LM339AD		SO-14	Tube	339 339A
LM339DT LM339ADT	0° C, +70° C	SO-14	Tape & reel	339 339A

TSSOP14



339A

339

339A

Tape & reel

8 Revision history

Table 8.	Document rev	ision history
----------	--------------	---------------

Date	Revision	Changes
01-Mar-2003	1	Initial release.
28-Apr-2009	2	Updated document format. Removed power dissipation from <i>Table 1: Absolute maximum</i> <i>ratings</i> . Added R _{THJA} , R _{THJC} , ESD and T _{LEAD} values to <i>Table 1</i> . Updated package information in <i>Chapter 6</i> . Added <i>Table 7: Order codes</i> .



Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2009 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan -Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

Doc ID 2159 Rev 2

